



Quick Look

|  |                           |   |
|--|---------------------------|---|
| Number of Ethernet WAN port                | 0 / 1 (GE) <sup>[1]</sup> | [1] Available with PrimeCare Subscription, complimentary for the first year. PrimeCare Enables Ethernet WAN, Wi-Fi WAN, Hot Failover, and Smoothing. Alternatively, without a PrimeCare Subscription, Feature pack license (MAX-BR1-MINI-FP) is required to activate the perpetual license for the aforementioned features. |
| Number of Ethernet LAN port                | 2 / 1 (GE) <sup>[1]</sup> | [1] Available with PrimeCare Subscription, complimentary for the first year. PrimeCare Enables Ethernet WAN, Wi-Fi WAN, Hot Failover, and Smoothing. Alternatively, without a PrimeCare Subscription, Feature pack license (MAX-BR1-MINI-FP) is required to activate the perpetual license for the aforementioned features. |
| Router Throughput                          | 300Mbps                   |   |
| SpeedFusion VPN Throughput (No Encryption) | 80Mbps                    |   |
| SpeedFusion VPN Throughput (256-bit AES)   | 60Mbps <sup>[2]</sup>     | [2] 60 Mbps by default for Firmware 8.4.1 or above.   |
| Number of Cellular Modem                   | 1                         |   |

Interfaces

|   |                                       |
|---|---------------------------------------|
| Maximum Ethernet WAN / LAN port configuration | 1 WAN with 1 LAN,<br>0 WAN with 2 LAN |
| SFP LAN / WAN                                 | No                                    |
| Serial Interface                              | Yes (RS232 & 485)                     |
| Wi-Fi AP                                      | Yes                                   |

|           |                    |
|-----------|--------------------|
| Wi-Fi WAN | Yes <sup>[1]</sup> |
|-----------|--------------------|

[1] Available with PrimeCare Subscription, complimentary for the first year. PrimeCare Enables Ethernet WAN, Wi-Fi WAN, Hot Failover, and Smoothing. Alternatively, without a PrimeCare Subscription, Feature pack license (MAX-BR1-MINI-FP) is required to activate the perpetual license for the aforementioned features.

|         |    |
|---------|----|
| USB WAN | No |
|---------|----|

|                  |    |
|------------------|----|
| Module Expansion | No |
|------------------|----|

## Performance

|                             |      |
|-----------------------------|------|
| Number of Recommended Users | 1–60 |
|-----------------------------|------|

|                                |    |
|--------------------------------|----|
| Maximum Number of AP Supported | No |
|--------------------------------|----|

## Wireless details

|                                 |          |
|---------------------------------|----------|
| Cellular Modem Category options | 1x CAT-4 |
|---------------------------------|----------|

|            |    |
|------------|----|
| 5G support | No |
|------------|----|

|           |   |
|-----------|---|
| SIM Slots | 2 |
|-----------|---|

|               |                |
|---------------|----------------|
| SIM Card Size | Nano-SIM (4FF) |
|---------------|----------------|

|             |                                      |
|-------------|--------------------------------------|
| Wi-Fi Radio | Dual (2.4GHz + 5GHz),<br>2x2 Wi-Fi 5 |
|-------------|--------------------------------------|

|  |       |
|--|-------|
| Wi-Fi Antenna Transmit Power<br>(2.4GHz, single chain) | 20dBm |
|--|-------|

|  |       |
|--|-------|
| Wi-Fi Antenna Transmit Power<br>(5GHz, single chain) | 20dBm |
|--|-------|

|                |    |
|----------------|----|
| Multiple SSIDs | 16 |
|----------------|----|

|     |     |
|-----|-----|
| GPS | Yes |
|-----|-----|

|                                  |    |
|----------------------------------|----|
| RemoteSIM (used in SIM Injector) | No |
|----------------------------------|----|

|           |    |
|-----------|----|
| FusionSIM | No |
|-----------|----|

|                         |                    |
|-------------------------|--------------------|
| Peplink eSIM Data Plans | Yes <sup>[3]</sup> |
|-------------------------|--------------------|

[3] Require Firmware 8.3.0 or above and supported for selected SKU.

BYO eSIM

Yes <sup>[4]</sup><sup>[4]</sup> Require Firmware 8.4.0 or above and supported for selected SKU.

## Features

SpeedFusion Hot Failover

Yes <sup>[1]</sup><sup>[1]</sup> Available with PrimeCare Subscription, complimentary for the first year. PrimeCare Enables Ethernet WAN, Wi-Fi WAN, Hot Failover, and Smoothing. Alternatively, without a PrimeCare Subscription, Feature pack license (MAX-BR1-MINI-FP) is required to activate the perpetual license for the aforementioned features.

SpeedFusion Smoothing

Yes <sup>[1]</sup><sup>[1]</sup> Available with PrimeCare Subscription, complimentary for the first year. PrimeCare Enables Ethernet WAN, Wi-Fi WAN, Hot Failover, and Smoothing. Alternatively, without a PrimeCare Subscription, Feature pack license (MAX-BR1-MINI-FP) is required to activate the perpetual license for the aforementioned features.

SpeedFusion Bandwidth Bonding

Yes <sup>[1]</sup><sup>[1]</sup> Available with PrimeCare Subscription, complimentary for the first year. PrimeCare Enables Ethernet WAN, Wi-Fi WAN, Hot Failover, and Smoothing. Alternatively, without a PrimeCare Subscription, Feature pack license (MAX-BR1-MINI-FP) is required to activate the perpetual license for the aforementioned features.

SpeedFusion Connect

Yes <sup>[5]</sup><sup>[5]</sup> PrimeCare subscription includes 500 GB/year complimentary SpeedFusion Connect Usage data.

SpeedFusion Relay Mode (Server)

Yes

Drop-In Mode

Yes

High Availability

Yes

Peplink AP Series Management

No

Remote AP & Multiple Config  
Profiles Management

No

WAN as LAN

Yes

LAN Bypass

No

InTouch

Yes

Virtual WAN

Yes <sup>[6]</sup><sup>[6]</sup> 1 Virtual WAN complimentary with active PrimeCare. Up to 3 Virtual WAN upon purchasing Virtual WAN Activation Licence.

Synergy Mode (Controller)

Yes

Synergized Device

Yes

Application and Web Blocking

Yes

|                       |      |
|-----------------------|------|
| Web Content Filtering | Lite |
|-----------------------|------|

|                |     |
|----------------|-----|
| IP Passthrough | Yes |
|----------------|-----|

|      |    |
|------|----|
| IPv6 | No |
|------|----|

|                   |                    |
|-------------------|--------------------|
| x.509 Certificate | Yes <sup>[7]</sup> |
|-------------------|--------------------|

[7] Require IPsec X.509 Certificate License Key

|                |     |
|----------------|-----|
| Captive Portal | Yes |
|----------------|-----|

|      |     |
|------|-----|
| GPIO | Yes |
|------|-----|

|                  |     |
|------------------|-----|
| Ignition Sensing | Yes |
|------------------|-----|

|                 |     |
|-----------------|-----|
| Netflow support | Yes |
|-----------------|-----|

|                            |    |
|----------------------------|----|
| LACP (802.3ad) NIC Bonding | No |
|----------------------------|----|

|                                     |    |
|-------------------------------------|----|
| Internal Storage for Edge Computing | No |
|-------------------------------------|----|

|                               |    |
|-------------------------------|----|
| External Storage via USB Port | No |
|-------------------------------|----|

|                |    |
|----------------|----|
| Dead Reckoning | No |
|----------------|----|

## Core Functionality

|                    |     |
|--------------------|-----|
| Inter-VLAN Routing | Yes |
|--------------------|-----|

|                        |    |
|------------------------|----|
| 802.1q VLANs Supported | 16 |
|------------------------|----|

|                 |     |
|-----------------|-----|
| Port-Based VLAN | Yes |
|-----------------|-----|

|                           |   |
|---------------------------|---|
| Load Balancing Algorithms | 8 |
|---------------------------|---|

|                           |     |
|---------------------------|-----|
| Load Balancing & Failover | Yes |
|---------------------------|-----|

|                        |    |
|------------------------|----|
| Inbound Load Balancing | No |
|------------------------|----|

|                              |     |
|------------------------------|-----|
| InControl 2 Cloud Management | Yes |
|------------------------------|-----|

|                                |     |
|--------------------------------|-----|
| InControl GPS Fleet Management | Yes |
|--------------------------------|-----|

## Advanced QoS Functionality

|                               |            |
|-------------------------------|------------|
| Bandwidth Usage Monitoring    | <b>Yes</b> |
| QoS for VoIP and E-Commerce   | <b>Yes</b> |
| User Groups Bandwidth Control | <b>Yes</b> |

## VPN Functionality

|   |                              |
|---|------------------------------|
| SpeedFusion VPN   | <b>Yes</b>                   |
| Number of SpeedFusion VPN Peers                           | <b>2 or 5</b> <sup>[8]</sup> |
| IPsec VPN   | <b>Yes</b>                   |
| Number of IPsec Tunnels                                   | <b>5</b>                     |
| L2TP VPN / Open VPN / PPTP VPN Server                     | <b>Yes</b>                   |
| Maximum PPTP / L2TP / OpenVPN Users                       | <b>3</b>                     |
| Remote RADIUS / LDAP authentication in Remote User Access | <b>No</b>                    |
| Number of OpenVPN Tunnel (Site to Site)                   | <b>5</b>                     |
| Number of GRE Tunnel (Site to Site)                       | <b>5</b>                     |

[8] 2 SpeedFusion VPN Peers are enabled by default. 5 SpeedFusion VPN Peers are enabled with PrimeCare Subscription, complimentary for the first year.

## Hardware

|  |                                  |
|--|----------------------------------|
| Enclosure  | <b>Compact,<br/>Indoor Metal</b> |
| 4pin Molex Micro-Fit Connector                                   | <b>Yes</b>                       |
| Terminal Block Power Connector for Mobile / Vehicular Deployment | <b>No</b>                        |

|                            |   |                     |
|----------------------------|---|---------------------|
| AC Adapter or PSU          | AC Input 100V–240V,<br>DC Output 12V 2A |                     |
| Input voltage              | DC 10–30V                               |                     |
| PoE Input                  | Yes <sup>[9]</sup>                      | [9] 1x 802.3at PoE. |
| PoE Output                 | No                                      |                     |
| USB Power Input            | No                                      |                     |
| Nominal Power Consumption  | 13W                                     |                     |
| Maximum Power Consumption  | 18W                                     |                     |
| Dimensions in inches       | 5.10 x 4.2 x 1.4 inches                 |                     |
| Dimensions in mm           | 129.5 x 107 x 35 mm                     |                     |
| Weight (Pound)             | 1.00 pound                              |                     |
| Weight (Gram / Kilogram)   | 455 grams                               |                     |
| Operating Temperature      | -40°–149°F,<br>-40°–65°C                |                     |
| Humidity                   | 15%–95% (non-condensing)                |                     |
| Rack-mount                 | No                                      |                     |
| Dual Hot Swap Power Supply | No                                      |                     |

Warranty Info

|          |                         |
|----------|-------------------------|
| Warranty | 1-Year Limited Warranty |
|----------|-------------------------|