





Quick Look

Number of Ethernet WAN port

0 / 1 (GE)

[1]

[1] Available with PrimeCare Subscription, complimentary for the first year. PrimeCare Enables Ethernet WAN, Wi-Fi WAN, Hot Failover, and Smoothing. Alternatively, without a PrimeCare Subscription, Feature pack license (MAX-BR1-MINI-FP) is required to activate the perpetual license for the aforementioned features.

Number of Ethernet LAN port

3 / 2 (GE)

[1]

[1] Available with PrimeCare Subscription, complimentary for the first year. PrimeCare Enables Ethernet WAN, Wi-Fi WAN, Hot Failover, and Smoothing. Alternatively, without a PrimeCare Subscription, Feature pack license (MAX-BR1-MINI-FP) is required to activate the perpetual license for the aforementioned features.

Router Throughput

300Mbps

SpeedFusion VPN Throughput (No Encryption)

80Mbps

SpeedFusion VPN Throughput (256-bit AES)

60Mbps

[2]

[2] 60 Mbps by default for Firmware 8.4.1 or above.

Number of Cellular Modem

1

Interfaces

Maximum Ethernet WAN / LAN port configuration

1 WAN with 2 LAN, 0 WAN with 3 LAN

SFP LAN / WAN

No

Serial Interface

No

Wi-Fi AP

Yes
Wi-Fi WAN
Yes
[1]
[1] Available with PrimeCare Subscription, complimentary for the first year. PrimeCare Enables Ethernet WAN, Wi-Fi WAN, Hot Failover, and Smoothing. Alternatively, without a PrimeCare Subscription, Feature pack license (MAX-BR1-MINI-FP) is required to activate the perpetual license for the aforementioned features.
USB WAN
No
Module Expansion
No

Performance

Number of Recommended Users
1–60
Maximum Number of AP Supported
No

Wireless details

Cellular Modem Category options
1x CAT-4, 1x CAT-6, 1x CAT-7
5G support
No
SIM Slots
2
SIM Card Size
Nano-SIM (4FF)
Wi-Fi Radio
Dual (2.4GHz + 5GHz), 2x2 Wi-Fi 5
Wi-Fi Antenna Transmit Power (2.4GHz, single chain)
20dBm
Wi-Fi Antenna Transmit Power (5GHz, single chain)
20dBm
Multiple SSIDs
16
GPS
Yes
RemoteSIM (used in SIM Injector)
Yes (HW4+)
FusionSIM
Yes (HW4+)
Peplink eSIM Data Plans
Yes (HW3+)
[3]
[3] Require Firmware 8.3.0 or above and supported for selected SKU.
BYO eSIM
Yes (HW3+)
[4]
[4] Require Firmware 8.4.0 or above and supported for selected SKU.

Features

SpeedFusion Hot Failover
Yes
[1]
[1] Available with PrimeCare Subscription, complimentary for the first year. PrimeCare Enables Ethernet WAN, Wi-Fi WAN, Hot Failover, and Smoothing. Alternatively, without a PrimeCare Subscription, Feature pack license (MAX-BR1-MINI-FP) is required to activate the perpetual license for the aforementioned features.

SpeedFusion Smoothing	
Yes	
[1]	
[1] Available with PrimeCare Subscription, complimentary for the first year. PrimeCare Enables Ethernet WAN, Wi-Fi WAN, Hot Failover, and Smoothing. Alternatively, without a PrimeCare Subscription, Feature pack license (MAX-BR1-MINI-FP) is required to activate the perpetual license for the aforementioned features.	
SpeedFusion Bandwidth Bonding	
Yes	
[1]	
[1] Available with PrimeCare Subscription, complimentary for the first year. PrimeCare Enables Ethernet WAN, Wi-Fi WAN, Hot Failover, and Smoothing. Alternatively, without a PrimeCare Subscription, Feature pack license (MAX-BR1-MINI-FP) is required to activate the perpetual license for the aforementioned features.	
SpeedFusion Connect	
Yes	
[5]	
[5] PrimeCare subscription includes 500 GB/year complimentary SpeedFusion Connect Usage data.	
SpeedFusion Relay Mode (Server)	
Yes	
Drop-In Mode	
Yes	
High Availability	
Yes	
Peplink AP Series Management	
No	
Remote AP & Multiple Config Profiles Management	
No	
WAN as LAN	
Yes	
LAN Bypass	
No	
InTouch	
Yes	
Virtual WAN	
Yes	
[6]	
[6] 1 Virtual WAN complimentary with active PrimeCare. Up to 3 Virtual WAN upon purchasing Virtual WAN Activation Licence.	
Synergy Mode (Controller)	
Yes	
Synergized Device	
Yes	
Application and Web Blocking	
Yes	
Web Content Filtering	
Lite	
IP Passthrough	
Yes	
IPv6	
No	
x.509 Certificate	
Yes	
[7]	
[7] Require IPsec X.509 Certificate License Key	
Captive Portal	
Yes	
GPIO	
Yes	
Ignition Sensing	
Yes	
Netflow support	
Yes	
LACP (802.3ad) NIC Bonding	
No	

Internal Storage for Edge Computing
No
External Storage via USB Port
No
Dead Reckoning
No

Core Functionality

Inter-VLAN Routing
Yes
802.1q VLANs Supported
16
Port-Based VLAN
Yes
Load Balancing Algorithms
8
Load Balancing & Failover
Yes
Inbound Load Balancing
No
InControl 2 Cloud Management
Yes
InControl GPS Fleet Management
Yes

Advanced QoS Functionality

Bandwidth Usage Monitoring
Yes
QoS for VoIP and E-Commerce
Yes
User Groups Bandwidth Control
Yes

VPN Functionality

SpeedFusion VPN
Yes
Number of SpeedFusion VPN Peers
2 or 5
[8]
[8] 2 SpeedFusion VPN Peers are enabled by default. 5 SpeedFusion VPN Peers are enabled with PrimeCare Subscription, complimentary for the first year.
IPsec VPN
Yes
Number of IPsec Tunnels
5
L2TP VPN / Open VPN / PPTP VPN Server
Yes
Maximum PPTP / L2TP / OpenVPN Users
3
Remote RADIUS / LDAP authentication in Remote User Access
No
Number of OpenVPN Tunnel (Site to Site)
5
Number of GRE Tunnel (Site to Site)
5

Hardware

Enclosure
Compact, Indoor Metal
4pin Molex Micro-Fit Connector
Yes
Terminal Block Power Connector for Mobile / Vehicular Deployment
No
AC Adapter or PSU
AC Input 100V–240V, DC Output 12V 2A
Input voltage
DC 12–30V
PoE Input
Yes
[9]
[9] 1x 802.3at PoE.
PoE Output
No
USB Power Input
No
Nominal Power Consumption
13W
Maximum Power Consumption
18W
Dimensions in inches
4.95 x 4.2 x 1.4 inches
Dimensions in mm
125.7 x 107 x 35 mm
Weight (Pound)
0.95 pounds
Weight (Gram / Kilogram)
430 grams
Operating Temperature
-40°–149°F, -40°–65°C
Humidity
15%–95% (non-condensing)
Rack-mount
No
Dual Hot Swap Power Supply
No

Warranty Info

Warranty
1-Year Limited Warranty