



Quick Look -

Number of Ethernet WAN port 0 / 1 (GE) [1]

[1] WAN port(s) can be configured as LAN port(s) via the Web Admin.

Number of Ethernet LAN port 1/0 (GE) [1]

[1] WAN port(s) can be configured as LAN port(s) via the Web Admin.

Router Throughput 300Mbps

SpeedFusion VPN Throughput (No

Encryption)

80Mbps

SpeedFusion VPN Throughput (256-

bit AES)

60Mbps

Number of Cellular Modem 2

number of Cellular Modem

Interfaces -

Maximum Ethernet WAN / LAN port 1 WAN with 0 LAN, configuration 0 WAN with 1 LAN

SFP LAN / WAN No

Serial Interface No

Wi-Fi AP No

Wi-Fi WAN No

USB WAN No

Module Expansion No

Tech Specs | Mobility ⋅ BR2 Micro



Performance -

Number of Recommended Users 1–60

Maximum Number of AP Supported **No**

Wireless details -

Cellular Modem Category options 2x CAT-4

5G support No

SIM Slots 2

SIM Card Size Nano-SIM (4FF)

Wi-Fi Radio No

Wi-Fi Antenna Transmit Power

(2.4GHz, single chain)

No

Wi-Fi Antenna Transmit Power

(5GHz, single chain)

No

Multiple SSIDs No

GPS Yes

RemoteSIM (used in SIM Injector) Yes

FusionSIM Yes

Peplink eSIM Data Plans

Yes [2] Models with selected SKU support eSIM.

BYO eSIM Yes [2] Models with selected SKU support eSIM.

Features

SpeedFusion Hot Failover

Yes [3] Require PrimeCare Subscription, complimentary for the first year.

SpeedFusion Smoothing
Yes [3] Require PrimeCare Subscription, complimentary for the first year.

SpeedFusion Bandwidth Bonding
Yes [3] Require PrimeCare Subscription, complimentary for the first year.

Tech Specs | Mobility • BR2 Micro



SpeedFusion Connect Yes [4] [4] PrimeCare subscription includes 500GB/year complimentary SpeedFusion Connect Usage data. SpeedFusion Relay Mode (Server) Yes Yes Drop-In Mode Yes High Availability Peplink AP Series Management No Remote AP & Multiple Config No Profiles Management WAN as LAN Yes No LAN Bypass InTouch Yes Yes [5] [5] 1 Virtual WAN complimentary with active PrimeCare. Up to 3 Virtual Virtual WAN WAN upon purchasing Virtual WAN Activation Licence. Synergy Mode (Controller) Yes Synergized Device Yes Application and Web Blocking Yes Web Content Filtering Lite Yes [6] [6] Available for Firmware 8.5.0 or above. IP Passthrough IPv6 No x.509 Certificate Yes Captive Portal Yes GPIO Yes **Ignition Sensing** Yes Netflow support Yes

Tech Specs | Mobility ⋅ BR2 Micro



LACP (802.3ad) NIC Bonding No

Internal Storage for Edge

Computing

No

External Storage via USB Port No

Dead Reckoning No

Core Functionality

Inter-VLAN Routing Yes

802.1q VLANs Supported 16

Port-Based VLAN Yes

Load Balancing Algorithms 8

Load Balancing & Failover Yes

Inbound Load Balancing No

InControl 2 Cloud Management Yes

InControl GPS Fleet Management Yes

Advanced QoS Functionality

Bandwidth Usage Monitoring Yes

QoS for VoIP and E-Commerce Yes

User Groups Bandwidth Control Yes

VPN Functionality

SpeedFusion VPN Yes

Number of SpeedFusion VPN Peers 2 or 5 [7]

[7] 2 SpeedFusion VPN Peers are enabled by default. 5 SpeedFusion VPN Peers are enabled with PrimeCare Subscription, complimentary for the first

Tech Specs | Mobility • BR2 Micro



Number of IPsec Tunnels

5

L2TP VPN / Open VPN / PPTP VPN Server

Maximum PPTP / L2TP / OpenVPN Users

Remote RADIUS / LDAP authentication in Remote User Access

Number of OpenVPN Tunnel (Site to Site)

Number of GRE Tunnel (Site to Site)

5

Hardware -

Enclosure	Indoor, Metal
4pin Molex Micro-Fit Connector	Yes
Terminal Block Power Connector for Mobile / Vehicular Deployment	No
AC Adapter or PSU	AC Input 100V–240V, DC Output 12V 2A
Input voltage	DC 10-30V
PoE Input	No
PoE Output	No
USB Power Input	Yes (9V)
Nominal Power Consumption	8W

13W

Maximum Power Consumption

Tech Specs | Mobility • BR2 Micro



Dimensions in inches 2.99 x 3.25 x 1.69inches

Dimensions in mm 76 x 83 x 43mm

Weight (Pound) 0.77 pounds

Weight (Gram / Kilogram) 350 grams

Operating Temperature -40°-149°F,

-40°-65°C

Humidity 15%–95% (non-condensing)

Rack-mount No

Dual Hot Swap Power Supply No

Warranty Info

Warranty 1-Year Limited Warranty